

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Original) A plasma display having an address electrode, a scan electrode and a sustain electrode, wherein cells are arranged at the intersection of the electrodes, including:

an initializing driver for initializing the cells; and

an address driver for selecting on-cells by applying data of a first voltage to the address electrode and a scan pulse of a second voltage to the scan electrode, and for selecting off-cells by applying data of a third voltage and the scan pulse to the scan electrodes, wherein the third voltage is higher than the first voltage.
2. (Original) The plasma display of claim 1, wherein the initializing driver supplies an identical waveform to both of the scan electrode and the sustain electrode.
3. (Original) The plasma display of claim 2, wherein the initializing driver simultaneously supplies a rising ramp waveform and a falling ramp waveform following the

rising ramp waveform to the scan electrode and the sustain electrode.

4. (Original) The plasma display of claim 3, wherein the initializing driver supplies the falling ramp waveform and a rising ramp waveform following the falling ramp waveform to the scan electrode, and supplies a fourth negative voltage to the sustain electrode.

5. (Original) The plasma display of claim 4, wherein the plasma display further includes a sustain driver for supplying the fourth voltage to the sustain electrode in the address period to select the on-cells and the off-cells.

6. (Currently Amended) The plasma display of claim 3 ~~or claim 4~~, wherein the falling ramp waveform falls from a first negative voltage to a second negative voltage, the absolute value of the second negative voltage being higher than that of the first negative voltage; and wherein the rising ramp waveform rises from the first negative voltage to zero(0)V.

7. (Original) The plasma display of claim 1, wherein the first voltage to select the on-

cells is any one of zero(0)V and the ground voltage GND; and wherein the second voltage is a positive voltage.

8. (Original) The plasma display of claim 1, wherein the plasma display further includes a sustain driver for applying alternately a sustain pulse of a fifth voltage to the scan electrode and the sustain electrode to occur a sustain discharge with respect to the on-cells.

9. (Original) A method of driving a plasma display having an address electrode, a scan electrode and a sustain electrode, wherein cells are arranged at the intersection of the electrodes, comprising:

initializing the cells;

selecting on-cells by applying data of a first voltage to the address electrode and a scan pulse of a second voltage to the scan electrode; and

selecting off-cells by applying data of a third voltage to the address electrode and the scan pulse to the scan electrode, wherein the second voltage is higher than the first voltage.

10. (Original) The method of claim 9, wherein the step of initializing the cells includes supplying an identical waveform to both of the scan electrode and the sustain electrode to make wall charges having an identical polarity accumulated on the scan electrode and the sustain electrode.

11. (Original) The method of claim 10, wherein the step of initializing the cells includes supplying simultaneously a rising ramp waveform and a falling ramp waveform following the rising ramp waveform to the scan electrode and the sustain electrode.

12. (Original) The method of claim 10, wherein the step of initializing the cells includes:

supplying a falling ramp waveform and a rising ramp waveform following the falling ramp waveform to the scan electrode; and

supplying a fourth negative voltage synchronized with the rising ramp waveform to the sustain electrode.

13. (Original) The method of claim 9, wherein the method further includes supplying the fourth voltage to the sustain electrode to select the on-cells and the off-cells, in the address period.

14. (Currently Amended) The method of claim 11 ~~or claim 12~~, wherein the falling ramp waveform falls from a first negative voltage to a second negative voltage, the absolute value of the second negative voltage being higher than that of the first negative voltage and wherein the rising ramp waveform rises from the first negative voltage to zero(0)V.

15. (Original) The method of claim 9, wherein the first voltage to select the on-cells is any one of zero(0)V and the ground voltage GND; and wherein the second voltage is a positive voltage.

16. (Original) The method of claim 9, the method further includes applying alternately a sustain pulse of a fifth voltage to the scan electrode and the sustain electrode to occur a sustain discharge with respect to the on-cells.

17. (Original) A driving method of a plasma display, including:
 - a reset period for initializing cells;
 - an address period for selecting the cells using a scan voltage of a first polarity and a data voltage of a second polarity; and
 - a sustain period for maintaining a discharge of the cells using the sustain voltage of the first polarity.

18. (Original) The method of claim 17, wherein the cells are initialized by an initializing voltage of the first polarity in the reset period.